

Parameters for Problem 5b

$$j := \sqrt{-1} \quad \text{dB} := 1 \quad G_p := 9 \cdot \text{dB}$$

$$M := \begin{bmatrix} 0.53 & 0.09 \\ 2.93 & 0.4 \end{bmatrix} \quad \phi := \begin{bmatrix} 178 \cdot \text{deg} & 48 \cdot \text{deg} \\ 76 \cdot \text{deg} & -56 \cdot \text{deg} \end{bmatrix} \quad m := 1..2 \quad n := 1..2 \quad S_{m,n} := M_{m,n} \cdot e^{j \cdot (\phi_{m,n} \cdot \text{rad})}$$

$$\Delta := S_{1,1} \cdot S_{2,2} - S_{2,1} \cdot S_{1,2} \quad |\Delta| = 5.235 \cdot 10^{-2} \quad \arg(\Delta) = -4.788 \cdot 10^1 \cdot \text{deg}$$

$$K := \left[\frac{1 - (|S_{1,1}|)^2 - (|S_{2,2}|)^2 + (|\Delta|)^2}{2 \cdot |S_{1,2} \cdot S_{2,1}|} \right] \quad K = 1.065$$

$$g_p := \frac{10^{(1 \cdot G_p)}}{(|S_{2,1}|)^2} \quad r_p := \frac{\sqrt{1 - 2 \cdot K \cdot |S_{1,2} \cdot S_{2,1}| \cdot g_p + (|S_{1,2} \cdot S_{2,1}|)^2 \cdot g_p^2}}{|1 + g_p \cdot [(|S_{2,2}|)^2 - (|\Delta|)^2]|} \quad C_p := \frac{g_p \cdot S_{2,2} - \Delta \cdot \overline{(S_{1,1})}}{1 + g_p \cdot [(|S_{2,2}|)^2 - (|\Delta|)^2]}$$

$$r_p = 6.413 \cdot 10^{-1} \quad C_p = 1.963 \cdot 10^{-1} + 2.839j \cdot 10^{-1} \quad |C_p| = 3.452 \cdot 10^{-1} \quad \arg(C_p) = 5.535 \cdot 10^1 \cdot \text{deg}$$

$$\theta := 0 \cdot \text{deg}, 20 \cdot \text{deg}.. 360 \cdot \text{deg} \quad \Gamma_L(\theta) := C_p + r_p \cdot e^{j \cdot \theta} \quad \Gamma_{in}(\theta) := S_{1,1} + \frac{S_{2,1} \cdot S_{1,2} \cdot \Gamma_L(\theta)}{1 - S_{2,2} \cdot \Gamma_L(\theta)} \quad \Gamma_s(\theta) := \overline{\Gamma_{in}(\theta)}$$

$$\Gamma_{out}(\theta) := S_{2,2} + \frac{S_{2,1} \cdot S_{1,2} \cdot \Gamma_s(\theta)}{1 - S_{1,1} \cdot \Gamma_s(\theta)} \quad \text{MAG}_{\Gamma_b}(\theta) := \left| \frac{\Gamma_{out}(\theta) - \overline{\Gamma_L(\theta)}}{1 - \Gamma_{out}(\theta) \cdot \overline{\Gamma_L(\theta)}} \right| \quad \text{VSWR}_{out}(\theta) := \frac{1 + \text{MAG}_{\Gamma_b}(\theta)}{1 - \text{MAG}_{\Gamma_b}(\theta)}$$

$$\theta := ((55.35 - 180) \cdot \text{deg}) \quad \Gamma_L := C_p + r_p \cdot e^{j\theta} \quad \Gamma_{in} := S_{1,1} + \frac{S_{2,1} \cdot S_{1,2} \cdot \Gamma_L}{1 - S_{2,2} \cdot \Gamma_L}$$

$$\Gamma_s := \overline{\Gamma_{in}} \quad \Gamma_{out} := S_{2,2} + \frac{S_{2,1} \cdot S_{1,2} \cdot \Gamma_s}{1 - S_{1,1} \cdot \Gamma_s}$$

$$\text{MAG}_{\Gamma_a} := \left| \frac{\Gamma_{in} - \overline{\Gamma_s}}{1 - \Gamma_{in} \cdot \overline{\Gamma_s}} \right| \quad \text{MAG}_{\Gamma_b} := \left| \frac{\Gamma_{out} - \overline{\Gamma_L}}{1 - \Gamma_{out} \cdot \overline{\Gamma_L}} \right| \quad \text{VSWR}_{in} := \frac{1 + \text{MAG}_{\Gamma_a}}{1 - \text{MAG}_{\Gamma_a}}$$

$$G_T := \left[\frac{1 - (\Gamma_s)^2}{(1 - \Gamma_{in} \cdot \Gamma_s)^2} \right] \cdot (S_{2,1})^2 \cdot \left[\frac{1 - (\Gamma_L)^2}{(1 - S_{2,2} \cdot \Gamma_L)^2} \right] \quad \text{VSWR}_{out} := \frac{1 + \text{MAG}_{\Gamma_b}}{1 - \text{MAG}_{\Gamma_b}}$$

$$G_P := \left[\frac{1}{(1 - (\Gamma_{in})^2)} \right] \cdot (S_{2,1})^2 \cdot \left[\frac{1 - (\Gamma_L)^2}{(1 - S_{2,2} \cdot \Gamma_L)^2} \right] \quad G_A := \left[\frac{1 - (\Gamma_s)^2}{(1 - S_{1,1} \cdot \Gamma_s)^2} \right] \cdot (S_{2,1})^2 \cdot \left[\frac{1}{(1 - (\Gamma_{out})^2)} \right]$$

$\frac{\theta}{\text{deg}} =$	$\text{VSWR}_{out}(\theta) =$
0	6.537
2·10 ¹	6.537
4·10 ¹	6.537
6·10 ¹	6.537
8·10 ¹	6.537
1·10 ²	6.537
1.2·10 ²	6.537
1.4·10 ²	6.537
1.6·10 ²	6.537
1.8·10 ²	6.537
2·10 ²	6.537
2.2·10 ²	6.537
2.4·10 ²	6.537
2.6·10 ²	6.537
2.8·10 ²	6.537

Answers for Problem 5b

$$|\Gamma_s| = 4.602 \cdot 10^{-1} \quad \arg(\Gamma_s) = -1.778 \cdot 10^2 \cdot \text{deg} \quad \Gamma_s = -4.599 \cdot 10^{-1} - 1.779j \cdot 10^{-2}$$

$$|\Gamma_{in}| = 4.602 \cdot 10^{-1} \quad \arg(\Gamma_{in}) = 1.778 \cdot 10^2 \cdot \text{deg} \quad \Gamma_{in} = -4.599 \cdot 10^{-1} + 1.779j \cdot 10^{-2}$$

$$|\Gamma_{out}| = 5.604 \cdot 10^{-1} \quad \arg(\Gamma_{out}) = -5.535 \cdot 10^1 \cdot \text{deg} \quad \Gamma_{out} = 3.187 \cdot 10^{-1} - 4.61j \cdot 10^{-1}$$

$$|\Gamma_L| = 2.961 \cdot 10^{-1} \quad \arg(\Gamma_L) = -1.246 \cdot 10^2 \cdot \text{deg} \quad \Gamma_L = -1.684 \cdot 10^{-1} - 2.436j \cdot 10^{-1}$$

$$\text{MAG}_{\Gamma_a} = 0 \quad \text{VSWR}_{in} = 1$$

$$\text{MAG}_{\Gamma_b} = 7.346 \cdot 10^{-1} \quad \text{VSWR}_{out} = 6.537$$

$$G_A = 1.726 \cdot 10^1 \quad 10 \cdot \log(G_A) = 1.237 \cdot 10^1 \cdot \text{dB}$$

$$G_P = 7.943 \quad 10 \cdot \log(G_P) = 9 \cdot \text{dB}$$

$$G_T = 7.943 \quad 10 \cdot \log(G_T) = 9 \cdot \text{dB}$$